



## LEADER 220 START 230V



### Overview

#### LEADER 220 START 230V

cod. 807539

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven vehicles. Characteristics: choice of normal charge, quick charge(BOOST), quick start \* display of charging and starting current \* protection against overloads and polarity reversal.



1 PH 230V



CAR



BOAT



TRACTOR



SMALL VAN



TRUCK



EXCAVATOR



VAN



CE MARKING



EAC CERTIFICATION



TÜV SUD CERTIFICATION

### Technical data



CODE 807539



MAINS VOLTAGE 230 V - 1 ph 50/60Hz



CHARGE/START POWER 0,8 / 3,6 kW



CHARGING VOLTAGE 12 / 24 V



EFFECTIVE CHARGING CURRENT 30 A



RATED CHARGE CURR. EN60335-2-29 20 A



START CURRENT 1V/C EN60335-2-29 120 A



MAX STARTING CURRENT 180 A



MIN./MAX RATED REFERENCE CAPACITY 30 / 400 Ah



ADJUSTMENT POSITIONS 2



DIMENSIONS 22,5 - 29 - 20,5 cm



WEIGHT 9 kg



## LEADER 220 START 230V



EAN CODE 800489788516 2



PIECES/PALLET 56 pz/pallet



PIECES/PALLET - B 42 pz/pallet - B

---

### Included Accessories

CABLE 6 MMQ 2 M AND WORK CLAMP - 123569

CABLE 6MMQ 2 M POSITIVE CLAMP - 123588